GENERAL NOTES

1. ALL RACEWAY SHALL BE CONCEALED UNLESS OTHERWISE NOTED.
2. THE SIZES OF ELECTRICAL RACEWAY SHALL BE AS INDICATED ON THE CONTRACT DRAWINGS AND SHALL MEET THE REQUIREMENTS OF THE LOCAL ELECTRIC CODE, ¾" MINIMUM, OR AS SHOWN ELSEWHERE.
3. ALL WIRE AND CABLE FOR POWER, LIGHTING, CONTROL INDICATION, ALARM, SIGNAL AND COMMUNICATION SYSTEM, UNLESS OTHERWISE NOTED, SHALL HAVE TYPE THHN INSULATION AND SHALL BE RATED FOR 600V MINIMUM.
4. ARCHITECTURAL DRAWINGS, INDICATE REQUIRED LOCATION OF WIRING DEVICES.
5. MINIMUM WIRE SHALL BE #12 FOR BRANCH CIRCUIT RUNS UP TO 100' TO THE LAST OUTLET; OVER 100'–#10; OVER 150'–#8 AND INCREASE CONDUIT SIZE AS REQUIRED BY LOCAL ELECTRICAL CODE.
6. ALL WIRING INSTALLATION SHALL BE COLOR CODED AS PER CODE. CONDUCTORS SIZED #10 AND LOWER SHALL BE SOLID; #8 AND HIGHER STRANDED.
7. PROVIDE EMPTY CONDUIT SYSTEM FOR TELEPHONE, COMPUTERS AND T.V. SYSTEMS. EQUIPMENT CABLING, TERMINATION DEVICES ETC. SHALL BE FURNISHED AND INSTALLED BY OTHERS. ALL CONDUITS SHALL BE 3/4" SIZE. PROVIDE #14 DRAG WIRE IN ALL EMPTY CONDUITS.
8. ALL WIRING DEVICES, PANEL BOARDS, DISTRIBUTION BOARDS, MOTORS, ETC., SHALL BE GROUNDED AS PER LOCAL ELECTRIC CODE.
9. ALL WORK SHALL BE INSTALLED IN FULL ACCORDANCE WITH LOCAL CODES, STATE AND LOCAL AUTHORITIES. FILE ALL PLANS, OBTAIN ALL PERMITS, PAY ALL FEES, SCHEDULE ALL INSPECTIONS, MAKE ALL TESTS AND OBTAIN ALL APPROVALS REQUIRED. THE ELECTRICAL WORK SHALL BE PERFORMED IN ACCORDANCE WITH THE LATEST EDITION OF NATIONAL ELECTRIC CODE AND LOCAL AUTHORITIES HAVING JURISDICTION. ALL COMPONENTS SHALL BE UL APPROVED AND LISTED.
10. WHERE CONFLICTS ARE FOUND BETWEEN DRAWINGS, SPECIFICATIONS, & LAWS & ORDINANCES, THE MOST STRINGENT SHALL APPLY.
11. SUBMIT FOR APPROVAL, COMPLETE SHOP DRAWINGS, LIST OF MATERIALS AND DETAILED DATA OF EQUIPMENT GIVING THE MANUFACTURERS NAME, CATALOG NUMBER, SIZE, CAPACITY AND DIMENSIONS. NO EQUIPMENT SHALL BE INSTALLED OR FABRICATED WITHOUT OBTAINING APPROVAL.
12. ALL MOTORS SHALL BE SUPPLIED WITH MOTOR STARTERS BY OTHERS UNLESS CLEARLY INDICATED OTHERWISE ON THE CONTRACT DOCUMENTS. THREE PHASE MOTORS SHALL BE PROVIDED WITH A COMBINATION MAGNETIC MOTOR STARTER WITH AMBIENT COMPENSATED OVERLOAD HEATERS IN EACH UNGROUNDED LEG. SHORT CIRCUIT PROTECTION SHALL BE BY MCP OR FUSED DISCONNECT SWITCH AS SHOWN OR SPECIFIED.
13. MANUALLY CONTROLLED SINGLE PHASE MOTORS SHALL HAVE FULLY RATED MANUAL MOTOR STARTER SWITCHES WITH O.L. HEATERS IN EACH UNGROUNDED LEG.
14. CIRCUIT RUNS ARE SHOWN DIAGRAMMATICALLY ONLY AND SHALL BE INSTALLED IN A MANNER TO PREVENT CONFLICTS WITH EQUIPMENT AND STRUCTURAL CONDITIONS. CONDUITS AND CABLES SHALL BE INSTALLED PARALLEL TO BEAMS AND WALLS.
15. CONDUITS SHALL BE TERMINATED SO AS TO PERMIT NEAT CONNECTIONS TO MOTORS AND OTHER EQUIPMENT.
16. THE QUANTITY AND SIZE OF WIRES AND CONDUIT SHOWN ON DRAWINGS AND WIRING DIAGRAMS REPRESENT A SUGGESTED ARRANGEMENT BASED UPON SELECTED STANDARD COMPONENTS OF ELECTRICAL EQUIPMENT. MODIFICATIONS ACCEPTABLE TO THE ENGINEER MAY BE MADE BY THE CONTRACTOR TO ACCOMMODATE EQUIPMENT ACTUALLY PURCHASED. THE BASIC SEQUENCE AND METHOD OF CONTROL MUST BE MAINTAINED AS INDICATED ON THE DRAWINGS.
17. SWITCHES SHALL BE MOUNTED 4'–0" MAX ABOVE FINISHED FLOOR UNLESS OTHERWISE NOTED. RECEPTACLES SHALL BE MOUNTED 1'–6" ABOVE FINISHED FLOOR UNLESS OTHERWISE NOTED.
18. ALL PANELBOARDS SHALL BE MOUNTED SO THAT THE DISTANCE FROM THE TOP CIRCUIT BREAKER OPERATING HANDLE TO THE FLOOR SHALL NOT EXCEED 6'–6".
19. REFER TO ARCHITECTURAL DRAWINGS FOR EXACT LIGHT FIXTURE LOCATIONS. LIGHTING FIXTURES SHALL BE MOUNTED ACCORDING TO THE MOUNTING HEIGHT GIVEN ON THE ARCHITECTURAL DRAWINGS, WITH THE DISTANCE BEING MEASURED FROM THE BOTTOM OF THE LIGHTING FIXTURE TO THE FINISHED FLOOR.
20. CONDUIT AND WIRE (NOT SHOWN) FOR THE HVAC CONTROL EQUIPMENT AND MISCELLANEOUS DEVICES, OUTLET, SWITCHES, JUNCTION, PULL AND TERMINAL BOXES SHALL BE PROVIDED WITH NEMA ENCLOSURE SUITABLE TO THE ENVIRONMENT.
21. ALL CONDUIT RUNS CROSSING EXPANSION JOINTS SHALL HAVE EXPANSION OR EXPANSION AND DEFLECTION TYPE FITTINGS.
22. SWITCHGEAR DESIGNATIONS ARE INTENDED TO BE INTERPRETED AS INDICATED BELOW.
    BLANK: NOT INTENDED FOR USE, PLATE ONLY.
    SPACE: CONTAINS NECESSARY BUS AND HARDWARE FOR FUTURE ADDITION OF BREAKERS OR STARTERS WITHIN SIZE RANGE SHOWN.
    SPARE: CONTAINS A COMPLETE BREAKER OR STARTER INSTALLED, SIZE AS INDICATED AVAILABLE FOR FUTURE USE.
23. CONDUIT FOR WIRING CONCEALED IN FLOOR SLABS, OR BELOW GRADE SHALL BE 1" MINIMUM.
24. CONFIRM EXACT POWER REQUIREMENTS AND CONNECTION LOCATIONS FOR ALL EQUIPMENT PROVIDED BY OTHERS WITH RESPECTIVE CONTRACTOR AND GENERAL CONTRACTOR PRIOR TO INSTALLATION.

BRANCH CIRCUIT WIRING

1. WIRING SHOWN ON DRAWINGS IS FOR SPECIFIC ROUTES OR SPECIAL CONDITIONS.
2. WIRING AND CONDUIT SHALL BE REQUIRED BETWEEN ALL OUTLETS INDICATED WITH CIRCUIT NUMBERS AND PANEL DESIGNATIONS.
3. ALL SWITCH CONTROLS SHALL BE PROVIDED WITH WIRING AND CONDUIT AS REQUIRED.
4. FOR CLARITY, ALL BRANCH CIRCUIT WIRE AND CONDUIT IS NOT SHOWN, HOWEVER A COMPLETE BRANCH CIRCUIT WIRING SYSTEM IS TO BE INSTALLED IN ACCORD WITH THE DEVICES AND CIRCUIT NUMBERS SHOWN.
5. ALL BRANCH CIRCUITS SHALL HAVE DEDICATED NEUTRALS. NO SHARED NEUTRALS WILL BE ALLOWED. A GREEN GROUNDING CONDUCTOR SHALL BE RUN WITH ALL CIRCUITS. VERIFY CONDUIT SIZE TO ENSURE IT CAN ACCOMMODATE ALL PHASE, NEUTRAL AND GROUND CONDUCTORS.

MEP COORDINATION

1. ALL ELECTRICALLY POWERED HVAC, PLUMBING AND FIRE PROTECTION EQUIPMENT TO BE PROVIDED WITH LOCAL DISCONNECT SWITCHES. THE SWITCHES SHALL BE PROVIDED BY THE E.C. UNLESS NOTED OTHERWISE.
2. DUCT MOUNTED SMOKE DETECTORS: ARE TO BE SUPPLIED BY THE E.C. (FIRE ALARM EQUIPMENT SUPPLIER), INSTALLED IN THE DUCTWORK BY THE HVAC SUBCONTRACTOR. WIRED BY THE E.C.
3. ALL MOTOR STARTERS ARE TO BE FURNISHED BY THE HVAC, PLUMBING OR FIRE PROTECTION SUBCONTRACTOR (TO DIVISION 16 SPECIFICATION REQUIREMENTS), INSTALLED AND WIRED BY THE E.C. STARTERS WILL BE MAGNETIC ACROSS THE LINE (AMBIENT COMPENSATED MOTOR OVERLOAD HEATERS IN ALL CURRENT CARRYING CONDUCTORS) WITH HOA SWITCH. MANUAL TOGGLE TYPE FOR SINGLE PHASE MOTORS WHICH DO NOT REQUIRE AUTOMATIC CONTROL.
4. SPEED CONTROL: FOR FRACTIONAL HORSEPOWER MOTORS THAT REQUIRE SPEED CONTROL, THE HVAC CONTRACTOR SHALL PROVIDE A LINE VOLTAGE SPEED CONTROL SWITCH
5. SPEED CONTROL: VARIABLE SPEED DRIVES (VSD) ARE SUPPLIED BY THE DRIVEN EQUIPMENT'S SUPPLIER, INSTALLED AND WIRED BY THE E.C.

POWER LEGEND

SYMBOLS	DESCRIPTION
	RECEPTACLE, DUPLEX
	RECEPTACLE, DUPLEX, FLUSH MOUNTED FLOOR BOX
M	MICROWAVE OUTLET, COORDINATE EXACT LOCATION WITH ARCHITECTURAL DETAILS
	RECEPTACLE, DOUBLE DUPLEX
AF	DUPLEX RECEPTACLE ARC FAULT
	RECEPTACLE, DUPLEX GFCI
X	DUPLEX GFCI RECEPTACLE MOUNTED 6" ABOVE COUNTER
WP	DUPLEX GFCI RECEPTACLE WITH WEATHER PROOF COVER/BOX
	DUPLEX RECEPTACLE BOTTOM HALF SWITCHED
	SPECIALTY OUTLET, SEE SCHEDULE
	SURFACE PANEL, NORMAL POWER
	FLUSH PANEL, NORMAL POWER
	HOMERUN TO PANEL
	FUSED DISCONNECT SWITCH, FUSE SIZE TO MATCH MFR. RECOMMENDATIONS
	LOCKABLE DISCONNECT SWITCH
	COMBINATION MOTOR STARTER WITH MOTOR PROTECTOR OVERLOADS, 120VAC CONTROLS, WITH HOA SELECTOR SWITCH
$_{HP}$	SAFETY SWITCH, HORSEPOWER RATED
R	RELAY
J	JUNCTION BOX
FA J	FIRE ALARM JUNCTION BOX
J	JUNCTION BOX WITH 4' WHIP
C J	CEILING BOX WITH BLANK COVER
FN J	CEILING FAN, PROVIDE JUNCTION BOX RATED FOR CEILING FAN SUPPORT WITH BLANK COVER
	CONTACTOR, ELECTRIC CHARACTERISTICS TO MATCH RESPECTIVE CIRCUIT
PB	PUSHBUTTON
DC	DIMMER CABINET
T	TRANSFORMER
DR	DOOR RELEASE, PROVIDE WIRING TO ELECTRIC STRIKE, STRIKE BY OTHERS
TC	TIMECLOCK
	FAN
	MOTOR
	PUMP
	ELEVATOR
	CONNECTION TO GROUND
	METER, UTILITY
CO	CARBON MONOXIDE DETECTOR
	APHONE INTERCOM STATION
CS	AREA OF REFUGE CALL STATION
AR	AREA OF REFUGE ANNUNCIATOR PANEL

RACEWAY LEGEND

SYMBOLS	DESCRIPTION
	CABLE TRAY
HH	HANDHOLE
	FLEXIBLE METAL CONDUIT
	CONDUIT/RACEWAY CONCEALED
	CONDUIT/RACEWAY TURNING UP
	CONDUIT/RACEWAY TURNING DN
CATV	CABLE TV CIRCUIT
FA	FIRE ALARM CIRCUIT
IMSA	MUNICIPAL FIRE ALARM CABLE
P	15 KV PRIMARY DUCTBANK
E	ELECTRIC
T	TELEPHONE SERVICE
SE	SERVICE ENTRANCE DUCTBANK
UGE	UNDERGROUND ELECTRIC
OHE	OVERHEAD ELECTRIC

LIGHTING LEGEND

SYMBOLS	DESCRIPTION
$	SINGLE POLE SWITCH
$M	WALL MTD MOTION DETECTOR/SENSOR, SINGLE CIRCUIT
$M2	WALL MTD MOTION DETECTOR/SENSOR DUAL CIRCUIT
$D	DIMMER SWITCH, WATTAGE TO MATCH RESPECTIVE CIRCUIT
$3	3-WAY SWITCH
$4	4-WAY SWITCH
$P	PILOT SWITCH
$LV	LOW VOLTAGE SWITCH, SINGLE CIRCUIT
$TM	TIMER SWITCH
M 900	INFRARED MOTION SENSOR
F1 a LP.2	2x4 FLUORESCENT LIGHTING FIXTURE CEILING OR RECESSED MOUNTED. "F1" INDICATES FIXTURE TYPE, "LP.2" INDICATES CIRCUIT NUMBER, "a" INDICATES SWITCH CONTROL.
	2x2 FLUORESCENT FIXTURE
	1x4 FLUORESCENT FIXTURE
	BATHROOM FAN LIGHT
	RECESSED DOWN LIGHT
	WALL MOUNTED LIGHT
	2' STRIP CEILING MOUNTED LIGHT
	INDIRECT FLUORESCENT FIXTURE
	WALL WASHER
	EMERGENCY FIXTURE, DENOTED BY SHADING
D	WALL SCONCE
	EMERGENCY LIGHTING BATTERY WITH 2 LAMP HEADS
	CEILING MOUNTED EXIT ARROW INDICATES DIRECTION
	WALL-MOUNTED EXIT ARROW INDICATES DIRECTION
	REMOTE EMERGENCY ADJUSTABLE WALL FIXTURE WITH 2 LAMP HEADS
PC	PHOTOCELL
DS	DOOR SWITCH

COMMUNICATION LEGEND

SYMBOLS	DESCRIPTION
	TELEPHONE OUTLET WITH 3/4" C. AND DRAG LINE RUN TO ACCESSIBLE LOCATION FOR FUTURE CABLING
	WALL TELEPHONE OUTLET WITH 3/4" C. AND DRAG LINE RUN TO ACCESSIBLE LOCATION FOR FUTURE CABLING
	TELEPHONE OUTLET, FLUSH MTD, FLOOR BOX WITH 3/4" C. AND DRAG LINE LINE RUN TO ACCESSIBLE LOCATION FOR FUTURE CABLING
P	PUBLIC TELEPHONE ADA COMPLIANT.
	DATA OUTLET WITH 3/4" C. AND DRAG LINE RUN TO ACCESSIBLE LOCATION FOR FUTURE CABLING
	TELEPHONE/DATA OUTLET WITH 3/4" C. AND DRAG LINE RUN TO ACCESSIBLE LOCATION FOR FUTURE CABLING
2/2	2 TELEPHONE/DATA OUTLETS W/ 3/4" C AND DRAG LINE RUN TO ACCESSIBLE LOCATION FOR FUTURE CABLING
	CATV OUTLET, WITH 3/4" C. AND DRAG LINE RUN TO ACCESSIBLE LOCATION FOR FUTURE CABLING
TV	CATV/DATA OUTLET WITH 3/4" C. AND DRAG LINE RUN TO ACCESSIBLE LOCATION FOR FUTURE CABLING
SP	CEILING SPEAKER
MAC	MEDIA ACCESS PANEL (FLUSH MOUNTED)

SUBSCRIPTS & ABBREVIATIONS

AF	ARC FAULT
AF	ABOVE FINISHED FLOOR
AIC	AMPERES INTERRUPTING CAPACITY
ATS	AUTOMATIC TRANSFER SWITCH
C	CONDUIT
CB	CIRCUIT BREAKER
CP	CONTROL PANEL
EC	ELECTRICAL CONTRACTOR
EMR	ELEVATOR MACHINE ROOM
EP	EMERGENCY POWER
E	EXISTING DEVICE TO REMAIN
ER	EXISTING DEVICE TO BE REMOVED
EX	EXISTING DEVICE TO BE RELOCATED
FBO	FURNISHED BY OTHERS
FACP	FIRE ALARM CONTROL PANEL
GC	GENERAL CONTRACTOR
GCP	GENERATOR CONTROL PANEL
GEC	GROUNDING ELECTRIC CONDUCTOR
GFI	GROUND FAULT INTERRUPTER (GFCI)
HOA	HANDS OFF AUTO SWITCH
LV	LOW VOLTAGE
LCP	LIGHTING CONTROL PANEL
M	MICROWAVE
MCB	MAIN CIRCUIT BREAKER
MDP	MAIN DISTRIBUTION PANEL
MLO	MAIN LUGS ONLY
MSB	MAIN SWITCH BOARD
NP	NORMAL POWER
NTS	NOT TO SCALE
TBD	TO BE DETERMINED
TC	TIME CLOCK
TP	TAMPER PROOF
TVSS	TRANSIENT VOLTAGE SURGE SUPPRESSION
U	UNDER COUNTER
VFD	VARIABLE FREQUENCY DRIVE
VSD	VARIABLE SPEED DRIVE
W	WALL MOUNTED
WP	WEATHER PROOF
X	ABOVE COUNTER TOP

FIRE ALARM LEGEND

SYMBOLS	DESCRIPTION
M	MASTER BOX
K	KNOX BOX
FJ	FIRE TELEPHONE JACK
ANN	FIRE ALARM REMOTE ANNUNCIATOR
P	PULL STATION
	SMOKE DETECTOR
ER	SMOKE DETECTOR, ELEVATOR RECALL
V/H	SMOKE DETECTOR 115V AC LOCAL DEVICE WITH SOUNDER BASE
H	SYSTEM SMOKE DETECTOR WITH SOUNDER BASE
DS	DUCT SMOKE DETECTOR
BM	BEAM DETECTOR
	HEAT DETECTOR, RATE OF RISE
135° F	HEAT DETECTOR, FIXED 135 DENOTES TEMPERATURE
15	STROBE 15 DENOTES CANDELA RATING
15 H	COMBINATION HORN-STROBE 15 DENOTES CANDELA RATING
M	MINI HORN
RTS	REMOTE TEST SWITCH WITH LED INDICATOR
R	REMOTE ALARM INDICATOR LED
FS	FLOW SWITCH
TS	TAMPER SWITCH
PS	PRESSURE SWITCH
DH	DOOR HOLDER
	EXTERIOR STROBE
CM	CONTROL MODULE
MM	MONITOR MODULE

DRAWING INDEX

DWG NO.	DESCRIPTION	REV
E0.0	ELECTRICAL NOTES & LEGEND	–
E0.1	ELECTRICAL SITE PLAN	–
E1.0	BASEMENT POWER PLAN	–
E1.1	FIRST FLOOR POWER PLAN	–
E1.2	SECOND FLOOR POWER PLAN	–
E1.3	ROOF POWER PLAN	–
E2.0	BASEMENT LIGHTING PLAN	–
E2.1	FIRST FLOOR LIGHTING PLAN	–
E2.2	SECOND FLOOR LIGHTING PLAN	–
E2.3	ROOF LIGHTING PLAN	–
E3.0	ONE LINE RISER DIAGRAM	–
E4.0	SCHEDULES	–
E5.0	DETAILS	–

LEGEND OF FEEDER SIZES–COPPER CONDUCTORS

FEEDER SYMBOL	CONDUCTORS (3 PHASE 3 WIRE) WITH GROUND	EMT RACEWAY	CONDUCTORS (3 PHASE 4 WIRE) WITH GROUND	EMT RACEWAY	NOMINAL AMPERE RATING
(1)	#6 & 1#10 GND.	3/4"			60
(2)			4#6 & 1#10 GND.	1"	
(3)	#4 & 1#8 GND.	1"			70
(4)			4#4 & 1#8 GND.	1-1/4"	
(5)	#2 & 1#8 GND.	1-1/4"			100
(6)			4#2 & 1#8 GND.	1-1/4"	
(7)	#1 & 1#6 GND.	1-1/4"			125
(8)			4#1 & 1#6 GND.	1-1/2"	
(9)	#1 1/0 & 1#6 GND.	1-1/2"			150
(10)			4# 1/0 & 1#6 GND.	1-1/2"	
(11)	#2 2/0 & 1#6 GND.	1-1/2"			175
(12)			4# 2/0 & 1#6 GND.	2"	
(13)	#3 3/0 &1#6 GND.	2"			200
(14)			4# 3/0 & 1#6 GND.	2"	
(15)	#4 4/0 & 1#4 GND.	2"			225
(16)			4# 4/0 & 1#4 GND.	2-1/2"	
(17)	3-250 KCML & 1#4 GND.	3"			250
(18)			4-250 LCML & 1#4 GND.	3"	
(19)	3-350 KCML & 1#4 GND.	3"			300
(20)			4-350 KCML & 1#4 GND.	3"	
(21)	3-500 KCML & 1#3 GND.	3"			350
(22)			4-500 KCML & 1#3 GND.	3-1/2"	
(23)	3-500 KCML & 1#3 GND.	3"			400
(24)			4-500 KCML & 1#3 GND.	3-1/2"	
(25)	6-250 KCML & 2#2 GND.	2 – 2-1/2"			500
(26)			8-250 KCML & 2#2 GND.	2-3"	
(27)	6-350 KCML & 2#1 GND.	2-3"			600
(28)			8-350 KCML & 2#2 GND.	2-3"	
(29)	6-600 KCML & 2#1/0 GND.	2 – 3-1/2"			800
(30)			8-600 KCML & 2#1/0 GND.	2-4"	
(31)	9-400 KCML & 3#1/0 GND.	3-3"			1000
(32)			12-400 KCML & 3#1/0 GND.	3-3"	
(33)	9-600 KCML & 2#1/0 GND.	3 – 3-1/2"			1200
(34)			12-600 KCML & 3#1/0 GND.	3-4"	
(35)	12-600 KCML & 4#4/0 GND.	4 – 3-1/2"			1600
(36)			16-600 KCML & 4#4/0 GND.	4-4"	
(37)	15-600 KCML & 5-250 KCML GND.	5 – 3-1/2"			2000
(38)			20-600 KCML & 5-250 KCML GND.	5-4"	
(39)	18-600 KCML & 6-350 KCML GND.	6 – 3-1/2"			2500
(40)			24-600 KCML & 6-350 KCML GND.	6-4"	
(41)	24-600 KCML & 8-400 KCML GND.	8 – 3-1/2"			3000
(42)			32-500 KCML & 6-400 KCML GND.	8 – 3-1/2"	
(43)	24-600 KCML & 8-400 KCML GND.	8 – 3-1/2"			3200
(44)			32-600 KCML & 8-500 KCML GND.	8-4"	
(45)	27-600 KCML & 9-500 KCML GND.	9 – 3-1/2"			3500
(46)			36-600 KCML & 9-500 KCML GND.	9-4"	
(47)	30-600 KCML &10-500 KCML GND.	10 – 3-1/2"			4000
(48)			400-600 KCML & 10-500 KCML GND.	10-4"	

CENTREPOINT ARCHITECTS
1 fitchburg street c308
somerville, ma 02143 t:617.718.9707

ALLIED
consulting engineering services, inc.
215 BOSTON POST ROAD
SUDBURY, MASSACHUSETTS 01776
Tel: (978) 443 7888
Fax: (978) 443 4636

The Village Shoppes of North Reading
303 Main Street
North Reading, MA

Permit

No.	ISSUE	DATE
1	PERMIT SET	5/30/08

PROJECT #: 28112

DRAWING TITLE: ELECTRICAL LEGEND & NOTES

E0.0